

A Fresh Look at Spatial Power Combining Oscillators

L. Wilson Pearson

Ronald J. Pogorzelski

(with liberal use of results of W. Wang, 1998)

January 4, 1999

Motivations for Presentation


- Spatial Power Combining is an enabling technology for achieving useful power levels from solid state devices at millimeter wavelengths
- Oscillator-based combining came first, historically, but has been passed over for what practitioners believe to be more reliable amplifier-based technology
- Recent results in oscillator-based combining systems offer possibilities for technology

breakthrough
January 4, 1999


Historical Overview of Spatial Power Combining

| “Pre-History” (spatial) | History (quasi-optic) |
|--------------------------------------|---------------------------------------|
| • Saiman, Breese and Patton, 1968 | • L. Wandinger, V. Nalbandian 1983 |
| • F. Durkin, 1981 | • Mink, 1986 |
| • Hyltin, <i>et. al.</i> , 1968 | • Popovic and Rutledge, 1988 |
| • All of phased array practice | • |

Why Combining is Necessary




Classic Circuit Combining




January 4, 1999

Efficiency Limitation in Wilkinson-Divider Tree




Feeding Incidental to PAE though Significant in Gain

Amplifiers/Oscillators



Caltech Grid Oscillator Format



January 4, 1999


State of the Art in Grid Oscillators

| Size | Devices | Frequency | Power | Institute |
|---------|-------------|-----------|-----------|--------------|
| 10×10 | FSC111LF | 5.0GHz | 550mW-ETP | Caltech |
| 4×4 | FSC111X | 11.6GHz | 335mW-ETP | Caltech |
| 6×6 | FSC111X | 17.0GHz | 235mW-ETP | Caltech |
| 5×5 | ATF35576 | 4.7GHz | 1.6W-ERP | Colorado |
| 10×10 | FLK052 chip | 9.8GHz | | Caltech |
| 2-10×10 | ATF35576 | 5.0GHz | 3.8W-ERP | Colorado |
| 4-10×10 | ATF35576 | 5.0GHz | 8.0W-ERP | Colorado |
| 2×3 | MESFET | 37.0GHz | 1mW | Georgia Tech |
| 6×6 | InP-HEMT | | 200mW-ERP | Caltech |
| 6×6 | FHX35LG | 4.4GHz | 2.56W-ERP | Clemson |


S.O.A. in Voltage Controlled Grid Oscillators

| Size | Frequency | Tuning Range | ERP | Power Variation | Authors |
|------|-----------|---------------|-------|-----------------|----------|
| 7x7D | 2.8GHz | 200MHz/7.1% | N/A | 24.6dB | Colorado |
| 7x7B | 6.0GHz | 616MHz/10.3% | N/A | 12.0dB | Colorado |
| 4x6B | 4.9GHz | 486MHz/9.9% | N/A | 2.0dB | Colorado |
| 4x4D | 12.4GHz | 200MHz/(1.5%) | N/A | N/A | Virginia |
| 4x4D | 4.9GHz | | 300mW | 8.0dB | Clemson |
| 6x6D | 6.3GHz | 350MHz/(5.5%) | 1.4W | N/A | Virginia |
| 4x4D | 4.7GHz | 330MHz/7% | 900mW | 10dB | Clemson |

Assemble & Go Coupled Oscillators




High-Q Resonators Require Tuning




January 4, 1999


Phase-locked Loop




Detector Pickup



Frequency Stabilization



Unlocked



Locked

$$f_0 = 4.643 \text{ GHz}$$

January 4, 1999

W. Wang, 1998

Other Results Bearing on Future Work


- High-Combining-Efficiency Microstrip Structure (Mortazawi)
- Phase Distribution Control (York, Pogorzelski, *et. al.*)
- Modulation (Wang)

Pogorzelski's Continuum Model

- Begins with Adler's difference equations, which describe a system of coupled oscillators
- Extends Adler's equations to a continuum, resulting in a Poisson's equation
- Demonstrates that Phase Perturbations Diffuse through an Array
- Intentional end perturbations lead to progressive phase shift

January 4, 1999

Coupled Oscillator Array



Coupled Oscillators

(Continued)

Define the phase of the i th oscillator, ϕ_i , by:

$$\theta_i = \omega_{ref} t + \phi_i$$

Then, the continuum model yields,

$$\frac{\partial^2 \phi}{\partial x^2} - \frac{\partial \phi}{\partial \tau} = - \frac{\omega_{tune} - \omega_{ref}}{\Delta \omega_{lock}} = -Cu(\tau)\delta(x-b)$$

Beamsteering Dynamics


Equal and opposite detuning of the end oscillators; i.e.,

$$\Delta\omega_L = -\Delta\omega_R = \Delta\omega_T$$

yields,


$$\phi(x, \tau) = \frac{\Delta\omega_T}{\Delta\omega_{lock}} \sum_{m=0}^{\infty} \frac{2 \sin(b\sqrt{\sigma_m}) \sin(x\sqrt{\sigma_m})}{(2a+1)\sigma_m} (1 - e^{-\sigma_m \tau})$$

Beamsteering Phase




January 4, 1999

Far Zone Radiation Pattern



January 4, 1999

Injection Locked Coupled Oscillator Array



Beamsteering via Injection

Define the phase by: $\theta_i = \omega_{ref} t + \phi_i$

$$\frac{d\phi_i}{dt} = \omega_{tune,i} - \omega_{ref} + \Delta\omega_{lock}(\phi_{i+1} - 2\phi_i + \phi_{i-1}) - \delta_{ip} \Delta\omega_{lock,p,inj}(\phi_p - \phi_{inj})$$

$$\frac{\partial^2 \phi}{\partial x^2} - \frac{\partial \phi}{\partial \tau} = -\frac{\omega_{tune} - \omega_{ref}}{\Delta\omega_{lock}} + \delta_{ip} \frac{\Delta\omega_{lock,p,inj}}{\Delta\omega_{lock}}(\phi - \phi_{inj})$$

Beam Steering

We injection lock two oscillators. The differential equation becomes

$$\frac{\partial^2 \phi}{\partial x^2} - [B_1 \delta(x - b_1) + B_2 \delta(x - b_2)] \phi - \frac{\partial \phi}{\partial \tau} = -B_1 \delta(x - b_1) p_1 u(\tau) - B_2 \delta(x - b_1) p_2 u(\tau)$$

The Laplace transform of the equation is,

$$\frac{\partial^2 F}{\partial x^2} - [B_1 \delta(x - b_1) + B_2 \delta(x - b_2)] F - sF = -B_1 \delta(x - b_1) \frac{P_1}{s} - B_2 \delta(x - b_1) \frac{P_2}{s}$$

Postulate,

$$F(x, s) = C_1 e^{-|x-b_1|\sqrt{s}} + C_2 e^{-|x-b_2|\sqrt{s}} + C_R e^{-x\sqrt{s}} + C_L e^{x\sqrt{s}}$$

Beam Steering Solution

The boundary conditions at the ends and the two injection points yield four equations for the four unknown constants and,

$$\begin{aligned}
 F(x, s) = & \frac{1}{s\Delta} \left\{ 2B_2p_2 \cosh[\sqrt{s}(2h - |b_2 - x|)] + 2B_2p_2 \cosh[\sqrt{s}(b_2 + x)] \right. \\
 & + 2B_1p_1 \cosh[\sqrt{s}(2h - |b_1 - x|)] + 2B_1p_1 \cosh[\sqrt{s}(b_1 + x)] \\
 & + \frac{B_1B_2p_2}{\sqrt{s}} \sinh[\sqrt{s}(2h - |b_2 - x|)] - \frac{B_1B_2p_1}{\sqrt{s}} \sinh[\sqrt{s}(2h - (b_2 - b_1) - |b_2 - x|)] \\
 & - \frac{B_1B_2p_2}{\sqrt{s}} \sinh[\sqrt{s}(2b_1 - |b_2 - x|)] - \frac{B_1B_2p_1}{\sqrt{s}} \sinh[\sqrt{s}((b_2 + b_1) - |b_2 - x|)] \\
 & + \frac{B_1B_2p_1}{\sqrt{s}} \sinh[\sqrt{s}(2h - |b_1 - x|)] - \frac{B_1B_2p_2}{\sqrt{s}} \sinh[\sqrt{s}(2h - (b_2 - b_1) - |b_1 - x|)] \\
 & \left. + \frac{B_1B_2p_1}{\sqrt{s}} \sinh[\sqrt{s}(2b_2 - |b_1 - x|)] + \frac{B_1B_2p_2}{\sqrt{s}} \sinh[\sqrt{s}((b_2 + b_1) + |b_1 - x|)] \right\}
 \end{aligned}$$

January 4, 1995

Beam Steering Continued

where,

$$\begin{aligned} \Delta = & 4\sqrt{s} \sinh[\sqrt{s}(2h)] \\ & + 2B_2 \cosh[\sqrt{s}(2b_2)] + 2B_1 \cosh[\sqrt{s}(2b_1)] + 2(B_2 + B_1) \cosh[\sqrt{s}(2h)] \\ & + \frac{B_1 B_2}{\sqrt{s}} \left\{ \sinh[\sqrt{s}(2h)] - \sinh[\sqrt{s}(2b_1)] + \sinh[\sqrt{s}(2b_2)] - \sinh[\sqrt{s}(2h - 2(b_2 - b_1))] \right\} \end{aligned}$$

The final value theorem yields,

$$\phi(x, \infty) = \frac{B_2 p_2 + B_1 p_1 + \frac{1}{2} B_1 B_2 [(b_2 - b_1)(p_2 + p_1) + (b_1 - x - |b_2 - x|)(p_2 - p_1)]}{B_2 + B_1 + B_1 B_2 (b_2 - b_1)}$$

Beam Steering Example

$$B_1 = B_2 = 1$$


$$b_1 = -h$$

$$b_2 = h$$

$$p_1 = -60^\circ$$

$$p_2 = 60^\circ$$

Beam Steering Example



January 4, 1999

Gradual Phase Change

- Step injection phase change limited to less than ninety degrees.
 - Yields extremely limited beam steering angles.
 - Can be mitigated by gradual phase change.
- Gradual change result can be obtained by convolution with a Gaussian.
 - Time domain solution is expressed as a sum of exponentials.
 - Convolution of a Gaussian and an exponential can be expressed as multiplication by a function involving complementary error functions.

Convolution with a Gaussian

$$\text{Let, } g(\tau) = e^{-\alpha(\tau-\tau_0)^2}$$

Then,

$$A_n e^{-\sigma_n^2 \tau} * g(\tau) = A_n e^{-\sigma_n^2 \tau} \left\{ e^{-\sigma_n^2 \tau_0} e^{\sigma_n^2/(4\alpha)} \frac{1}{\sqrt{\pi\alpha}} [\operatorname{erfc}(v_1) - \operatorname{erfc}(v_2)] \right\}$$


where,

$$v_1 = -\sqrt{\alpha} \left(\tau_0 + \frac{\sigma_n}{2\alpha} \right)$$
$$v_2 = \sqrt{\alpha} \left[\tau - \left(\tau_0 + \frac{\sigma_n}{2\alpha} \right) \right]$$

Gradual Steering Example


Choose, $\tau_0 = 6.0$

$\alpha = 0.01$




January 4, 1999

Far Zone Field




January 4, 1999


Phase Modulation



Modulation Out of Band to PLL




Received 1MHz signal




Spectrum of 1MHz modulation

Modulation Frequency In Band



Received 10kHz signal



Spectrum of 10kHz modulation

Constraints on Pulse Train

- The PLL integrates the modulation train and drifts according to the mean value of the train. => Zero-mean sequence
- The data rate in the pulse train must be much larger than the bandwidth of the PLL

Generic Replacement for a Phased Array

